

# Assign Phone Feature Buttons (User Portal)

Last Modified on 01/26/2018 11:47 am EST

You can configure any available flex buttons on your iPECS desktop phone for quick access to features that you use often. (Your phone comes with some pre-assigned flex buttons that you cannot change.)

## Add flex buttons

1. In your browser, go to the [iPECS Cloud User Portal](#) and log in.
2. Expand My Phone & Features and click Phone Configuration. Scroll down to the list of flex button assignments. (You can see the same list of buttons on the phone itself by pressing the phone's OK button.)

Phone Configuration		DN Call Failover				
	<input type="checkbox"/> Button Class	Button Type	Phone No.	Dial Digit	Button Label	Digit Number Setting
1	<input type="checkbox"/>	DN Number	69627737			
2	<input type="checkbox"/>	DN Number	27737			
3	<input type="checkbox"/>	DN Number	201		201	
4	<input type="checkbox"/>	No Assign				
5	<input type="checkbox"/>	No Assign				
6	<input type="checkbox"/>	No Assign				
7	<input type="checkbox"/>	No Assign				
8	<input type="checkbox"/>	No Assign				
9	<input type="checkbox"/>	No Assign				

Each row corresponds to a flex button on your phone.

- A flex button without a checkbox is pre-assigned and cannot be changed.
- A flex button labeled "No Assign" is not in use and can be assigned a feature.

3. Select an available flex button and click Modify.

### Flexible Button Add

Site Name	Main
Phone	27737 (LIP-9030 (B061C7115468))
Button Number	4
Button Class	Fixed Button
Button Type	REDIAL
Button Label	

**Save** **Close**

3. Select Button Class:

- Fixed Button creates a feature flex button:
  - For Button Type: Select the feature to assign (REDIAL, SPEED, CONFERENCE, MUTE, CALLBACK, DND/CALL FORWARD, TRANSFER, FLASH, PTT).
- Digit creates a Speed Dial flex button.
  - For Dial Digit, enter the specific speed dial number that will be dialed when the button is pressed.

4. Type the Button Label that will be displayed on the phone's LCD next to the flex button.

5. Click Save.